

## PMH 10XX Series Metal Material Power Inductor

### Features

- Metal material for large current and low DCR of super performance.
- Ultra low buzz noise due to molding construction type.
- Closed magnetic circuit design reduces leakage flux.



### Applications

- Notebooks, tablets
- Telecom Base Station, Industrial Control Board, Motor Control and etc.
- Server, DC-DC power for FPGA and etc.


### Yint P/N Information

① PM    ② H    ③ 1030    ④ -R22    ⑤ M    ⑥ 0    ⑦ T


- ① Product series
- ② Material
- ③ Size
- ④ Inductance
- ⑤ Tolerance
- ⑥ Special code
- ⑦ Taping information

④ Nominal Inductance[ $\mu$ H]	
Example	Nominal Value[ $\mu$ H]
R22	0.22 $\mu$ H
1R0	1.0 $\mu$ H
100	10 $\mu$ H
⑤ Inductance Tolerance	
M	$\pm$ 20%

### Shape & Dimension information



### <Recommend Land Pattern>



Unit: mm

Series	Dimensions					Land Pattern (Typ.)		
	A	B	C	D	E	a	b	c
PMH1030	11.5 max.	10.0 $\pm$ 0.3	2.8 $\pm$ 0.2	3.0 $\pm$ 0.5	2.0 $\pm$ 0.5	5.4	13.6	4.1
PMH1040	11.5 max.	10.0 $\pm$ 0.3	3.8 $\pm$ 0.2	3.0 $\pm$ 0.5	2.0 $\pm$ 0.5	5.4	13.6	4.1
PMH1050	11.5 max.	10.0 $\pm$ 0.3	4.8 $\pm$ 0.2	3.0 $\pm$ 0.5	2.0 $\pm$ 0.5	5.4	13.6	4.1

## PMH 10XX Series Metal Material Power Inductor

## Specification information

Yint P/N	Inductance	DC Resistance	Saturation Current	Heating Rating Current
	L0 (μH)	DCR (mΩ)	Isat (A)	Irms (A)
	100 kHz, 1V	Max.	Typ.	Typ.
PMH1030-R22M0T	0.22	1.2	50	33
PMH1030-R33M0T	0.33	1.6	32	23
PMH1030-R36M0T	0.36	1.6	28	23
PMH1030-R47M0T	0.47	2.5	26	22
PMH1030-1R0M0T	1	6	21	15
PMH1030-2R2M0T	2.2	9	14	11
PMH1030-3R3M0T	3.3	16	12	9
PMH1030-4R7M0T	4.7	24	10	7
PMH1030-8R2M0T	8.2	45	7	5
PMH1030-330M0T	33	160	4	2.6
-	-	-	-	-
PMH1040-R15M0T	0.15	0.65	75	45
PMH1040-R22M0T	0.22	1	60	35
PMH1040-R30M0T	0.3	1.1	45	35
PMH1040-R36M0T	0.36	1.2	45	30
PMH1040-R47M0T	0.47	1.7	40	30
PMH1040-R56M0T	0.56	1.8	33	25
PMH1040-R68M0T	0.68	2.4	30	23
PMH1040-R80M0T	0.8	2.7	29	23
PMH1040-1R0M0T	1	3.3	28	19
PMH1040-1R5M0T	1.5	4.2	24	16
PMH1040-2R2M0T	2.2	7	16.5	12
PMH1040-3R3M0T	3.3	11.8	16	11
PMH1040-4R7M0T	4.7	20	13	9
PMH1040-6R8M0T	6.8	25	12	8.5
PMH1040-8R2M0T	8.2	27	9	8
PMH1040-100M0T	10	30	8.5	7.8
PMH1040-150M0T	15	45	7	6.5
PMH1040-220M0T	22	66	5.5	5
PMH1040-330M0T	33	92	4.8	4.4
PMH1040-470M0T	47	145	3.5	3.3
PMH1040-680M0T	68	195	3	2.5
PMH1040-820M0T	82	285	2.8	2.3
PMH1040-101M0T	100	340	2.3	2

## PMH 10XX Series Metal Material Power Inductor

### Specification information

Yint P/N	Inductance	DC Resistance	Saturation Current	Heating Rating Current
	L0 (μH)	DCR (mΩ)	Isat (A)	Irms (A)
	100 kHz, 1V	Max.	Typ.	Typ.
PMH1050-R22M0T	0.22	0.8	65	37
PMH1050-1R0M0T	1	3	30	23
PMH1050-1R5M0T	1.5	3.8	25	21
PMH1050-2R2M0T	2.2	6	19	15
PMH1050-3R3M0T	3.3	10	16	13
PMH1050-4R7M0T	4.7	14	15	11
PMH1050-5R6M0T	5.6	17	14	9.5
PMH1050-6R8M0T	6.8	18.5	14	9
PMH1050-100M0T	10	28	10	8
PMH1050-150M0T	15	42	7.5	6.5
PMH1050-220M0T	22	50	6	5.5
PMH1050-330M0T	33	86	5.2	4.8
PMH1050-470M0T	47	127	4.5	3.7
PMH1050-101M0T	100	290	2.8	2.1

### Testing Conditions:

- 1.All test data is base on 25 °C ambient .
- 2.Operating temperature range - 55 °C to + 125 °C.
- 3.Irms (A):DC current will cause an approximate ΔT of 40 °C base on 25 °C ambient temperature.
- 4.Isat(A): DC current will cause L0 to drop approximately 30 %.
- 5.The part temperature (ambient + temp rise) should not exceed 125 °C under worst cases.

### Reel & QTY information

Series	MPQ(Pcs)	Reel (W / P)
PMH1030	800	13" (24 / 16)
PMH1040	500	13" (24 / 16)
PMH1050	500	13" (24 / 16)